



LF10 Access Control Device Kit



LF10 Access Control Device

Features

- Communication: TCP/IP, USB-host
- Standard advanced access control function to ensure the safe of working environment
- Support for multiple validation methods, demonstrating safety and efficiency

Specification

Display	2.4" TFT Color Screen
User Capacity	1,500 (optional card: 5,000)
FingerPrint Capacity	1,500
Card Capacity	5,000 (Optional) ID / Mifare card
Transaction Capacity	80,000
Power Supply	DC 12V 1.5A
Communication	TCP/IP, USB-host
Standard Function	Record Checking, Automatic Status Switch, Advanced Access Control, Wired doorbell, Wiegand Out
Operating Temperature	0 °C - 45 °C
Operating Humidity	20% - 80%
Dimensions	83*180.09*33.2mm
Software	ZKBioAccess



LM-2805 Electromagnetic Lock

Features

- Can withstand 200kg-220kg closing force;
- U, L, Z, ZL mounting brackets are available;
- Can be installed in metal doors, wooden doors and glass doors;
- With signal feedback function;

Specification

Input voltage	DC12V
Working current	480mA ± 5 %
Tensile force range	200kg ± 5 %
Weight	1.77kg
Lock body size	250x 47 x 25.5mm
Iron plate size	180x 38x 11mm
Interface Description	V+ - positive power supply; V- - negative power supply; Feedback signal output: NO/COM/NC



LMB-280U U

For frameless glass doors
Size: 180*43*28 mm

* This lock bracket is included in the package and do not need to be purchased separately.

TLEB102 Exit Button

Features

NO/NC/COM; Touchless Sensor;

Specification

Switching voltage	DC 9 ~ 16V
Rated current	2A
Operating temperature	-20°C ~ +50°C
storage temperature	-20°C ~ +65°C
Working humidity	10%-90%
shell material	SUS304 stainless steel material
Infrared sensing distance	2-10CM
Size	Length 115* width 70* height 38mm



Packing list

Pack A	Model	Code	Quantity
Access Control Device (ZKTeco label)	LF10	F02010811	1
Electromagnetic lock	LM-2805	X01601010	1
Lock bracket	LMB-280U	X01603005	1
Exit button	TLEB102	X01501055	1
RFID Card	I D Card	X00101001	10



Configuration



Usage scenario



Electromagnetic lock

Lock bracket

Exit button

